

Panda 4000s.Neo PMS marine generator

**The ideal entry level generator -
easy to install and non-stop energy**

The new Panda 4000s.Neo PMS generator is an ideal entry level generator and features the Fischer Panda water-cooled FPE320 single cylinder engine.

It is very compact designed for skippers who only have limited space available.

The Panda 4000s.Neo PMS is ideal for powering domestic electrical consumers with 230 V / 50 Hz - for anyone who wants to cook electrically, use a vacuum cleaner, hair dryer or coffee machine.

- 230 V / 50 Hz...
for your complete on-board power system
- Very compact and light...
more room for you
- Super-silent sound insulation capsule...
you can relax while the generator works
- Innovative Design...
easy to install and maintain with all connections on one side
- High starting capacity...
perfect for a compressor or air conditioner



Panda Generator 4000s.Neo



Panda P4-Control Panel





Generator

Model	Panda 4000s.Neo PMS	
Dimensions (LxWxH)	[mm]	558 x 460 x 518
Weight	[kg]	92
Sound level (7m / 3m / 1m)	[dB]	54 / 64 / 69
Cooling System	Dual circuit - freshwater cooling via heat exchanger	

Performance

Nominal Output	[kW]	3.4 kW / 4.0 kVA
Voltage Stability	[%]	230 V ± 5 %
Frequency Stability	[%]	50 Hz ± 2 Hz

Control

Starter System	12 V electric start
Remote Control Panel	Panda P4 Control

Engine

Engine Manufacturer	Fischer Panda	
Engine Type	FPE320	
Engine Displacement	[ccm]	309
Speed	[rpm]	3000

Disclaimer: The information contained here is to the best of our knowledge accurate at the date of publication. All products are subject to continuous development and Fischer Panda GmbH reserves the right to alter technical specifications without prior notice.

Version: 06/2017



Fischer Panda UK Ltd.
17 Blackmoor Road,
Ebblake Estate, Verwood
Dorset. BH31 6AX

Tel. : 01202 820 840
Fax : 01202 810 082
Email : info@fischerpanda.co.uk
Web : www.fischerpanda.co.uk

